



## BIOS Update Readme

### BIOS Update Instructions for Intel® Desktop Boards

This Readme file includes BIOS update instructions for advanced users. If you need more complete step-by-step instructions on how to use each of these BIOS update methods, refer to <http://support.intel.com/support/motherboards/desktop/sb/CS-022312.htm>.

To identify your current BIOS version, check the BIOS version string:

1. During boot, enter the BIOS setup by pressing **F2**.
2. Check the **Main** menu. The third segment of the BIOS ID string (a 4-digit number) is the current BIOS version.
3. Press **Escape** to exit BIOS Setup.

Example BIOS ID string showing the version number:

System Setup					
Main	Advanced	Security	Power	Boot	Exit
BIOS Version	BIG4110H.86A.0012.2009.1217.1928				
Processor Type	Genuine Intel® CPU 2160 @ 1.80GHz Intel® 64 Architecture Capable				
Core Multiplexing Technology	[Enable]				
Processor Speed:	1.80 GHz				
System Bus Speed	800 MHz				
L2 Cache RAM	1024 KB				

There are up to six methods of updating an Intel® Desktop Board BIOS to the latest version. The number of options made available for any particular board may vary depending on BIOS support, drive support and BIOS update file size. You only need to use one.

- Express BIOS Update
- F7 BIOS Flash Update
- Recovery BIOS Update
- Integrator Toolkit BIOS Files

#### Important Notes:

- Update the BIOS on your computer only if the newer BIOS version specifically solves a problem you have. We do not recommend BIOS updates for computers that do not need it. You can view all BIOS changes in the Release Notes included on the BIOS download page in Download Center.
- Downgrading the BIOS to an earlier version is not recommended and may not be supported. An earlier BIOS version may not contain the support for the latest processors, bug fixes, critical security updates, or support the latest board revisions currently being manufactured.
- Before initiating a BIOS update, be sure to read and precisely follow the instructions included in this document. You may wish to print the instructions for easy reference.

- If a BIOS update process is interrupted, your computer may not function properly. We recommend the process be done in an environment with a steady power supply (preferably with UPS).
  - Before updating the BIOS on the Intel® Desktop Board, manually record all BIOS settings that have been changed (from default) so they can be restored after completing the BIOS update.
- 

### **Instructions for Express BIOS Updates**

With the Intel Express BIOS Update utility you can update the BIOS while in the Windows environment. The BIOS file is included in an automated update utility that combines the functionality of the Intel® Flash Memory Update Utility and the ease-of use of Windows-based installation wizards.

1. Save the Express BIOS update file to a temporary directory on the target PC.
2. Double-click the \*.EXE file to run the Express BIOS update.

**CAUTION!!! DO NOT POWER DOWN YOUR SYSTEM** before the update is complete. This update will take up to 3 minutes.

---

### **Instructions for F7 BIOS Flash Update**

The F7 BIOS Flash Update is available on Intel® Desktop Boards beginning in 2009. To see if your board supports this feature, in BIOS Setup, check the Advanced > Boot Configuration menu for the setting **Display F7 to Update BIOS**.

1. Download and save the Recovery BIOS (.BIO) file to a temporary directory.
  2. Copy the .BIO to a USB thumb drive.
  3. Plug the thumb drive into a USB port of the target computer.
  4. Shut down the target computer.
  5. Enable the F7 prompt display:
    - a. Power the computer on.
    - b. Enter the BIOS Setup by pressing F2 during boot.
    - c. Go to the Advanced > Boot Configuration menu.
    - d. Enable **Display F7 to Update BIOS**
    - e. Press F10 to save and exit.
  6. During boot, when the F7 prompt is displayed, press F7 to enter the BIOS Flash Update tool.
  7. Select the USB thumb drive and press Enter.
  8. Select the .BIO file and press Enter
  9. Confirm you want to update the BIOS by pressing Enter.
  10. Wait 2-5 minutes for the update to complete.
  11. Remove the thumb drive.
  12. Restart the computer.
- 

### **Instructions for Recovery BIOS Updates**

In the unlikely event that a BIOS update is interrupted, it is possible the BIOS may be left in an unusable state. The recovery process requires the chassis to be opened to move the onboard BIOS Configuration Jumper.

**WARNING:** This process is intended to be performed by a trained technician.

#### Recovery with Bootable USB Thumb Drive

Use this method if the recovery file (\*.BIO) is too large to fit on a floppy disk or if the desktop board does not include floppy drive support.

1. Copy the recovery file (\*.bio) to a bootable USB thumb drive.
  2. Place the thumb drive in a USB port of the target system.
-

3. Shut down the system and unplug AC power.
4. Open the chassis and remove the BIOS Configuration Jumper. See the Technical Product Specification for details including the location of this jumper.
5. Power the system on.
6. Wait 2-5 minutes for the update to complete.
7. System will either turn off when the recovery process is completed or it will prompt you to turn off the system.
8. Remove the thumb drive from the USB port.
9. Replace the BIOS Configuration Jumper.
10. Restart system.

#### Recovery with CD-ROM

Use this method if the recovery file (\*.BIO) is too large to fit on a floppy disk or if the desktop board does not include floppy drive support.

1. Copy the recovery file (\*.bio) to a CD.
2. Place the CD in the CD-ROM drive of the target system.
3. Shut down the system and unplug AC power.
4. Open the chassis and remove the BIOS Configuration Jumper. See the Technical Product Specification for details including the location of this jumper.
5. Power the system on.
6. Wait 2-5 minutes for the update to complete.
7. System will either turn off when the recovery process is completed or it will prompt you to turn off the system.
8. Replace the BIOS Configuration Jumper.
9. Restart system.

#### Recovery with Floppy Disk

Use this method if the recovery file (\*.BIO) is small enough to fit on a floppy disk (smaller than 1.44MB) and the desktop board includes floppy drive support. Note: The floppy disk does NOT need to be bootable; however, it must be formatted.

1. Copy the recovery file (\*.bio) to a formatted floppy disk.
2. Place the disk in the floppy drive (drive A) of the target system.
3. Shut down the system and unplug AC power.
4. Open the chassis and remove the BIOS Configuration Jumper. See the Technical Product Specification for details including the location of this jumper.
5. Power the system on.
6. Wait 2-5 minutes for the update to complete. When the floppy drive LED is lit, the system is copying the recovery code into the FLASH device.
7. System will either turn off when the recovery process is completed or it will prompt you to turn off the system.
8. Remove floppy disk from drive A:
9. Replace the BIOS Configuration Jumper.
10. Restart system.

NOTE: If the error message "CMOS/GPNV Checksum Bad...Press F2 to Run SETUP" appears during boot after the update, press [F2] to go into the "BIOS Setup Utility", press [F9] to load setup defaults, and then press [F10] to save and exit.

---

---

#### **Instructions for Integrator Toolkit BIOS Files**

With the Iflash BIOS Update / Integrator Toolkit BIOS Files you can update the BIOS from a bootable CD-ROM, bootable USB flash drive or other bootable USB media. This download also provides the necessary files for Intel® Integrator Toolkit.

CAUTION!!! DO NOT POWER DOWN YOUR SYSTEM before the update is complete. This update will take up to 3 minutes.

#### iFlash Update with CD-ROM or USB Device

Use this method if the files are too large to fit on a floppy disk or if the desktop board does not include floppy drive support. You will need a CD or a USB device, such as a USB thumb drive or USB external hard drive.

1. Download and save the Integrator Toolkit BIOS Files to a temporary directory.
2. Double-click the \*.EXE to extract necessary files.
3. Copy the .BIO file and IFLASH2.EXE to a CD-ROM or USB device.
4. Boot the target PC to DOS.
5. At the appropriate directory prompt for the CD-ROM drive or USB drive, type **IFLASH2 /pf XXX.BIO /rb** (where XXX.BIO is the filename of the .BIO file) to launch the iFlash BIOS update process.

Note: The Integrator Toolkit BIOS Files download also provides the \*.ITK file necessary for use with the Intel® Integrator Toolkit.

---

---

#### **Creating a Bootable USB Device**

Making a USB flash device into a bootable drive is not as simple as creating bootable floppy disks. Please refer to the documentation provided by the manufacturer of your USB device for information on how to create a bootable USB device. Additionally, you may refer to any of the following websites for tips on creating bootable USB devices. Intel is unable to assist with the creation of bootable devices.

- Make your Thumb Drive Bootable at <http://www.pcmag.com/article2/0,1895,1846793,00.asp>
- How to Boot from a USB Device at [http://www.weethet.nl/english/hardware\\_bootfromusbstick.php](http://www.weethet.nl/english/hardware_bootfromusbstick.php)

You can also search for additional resources on the web for creating bootable USB devices. Search on “How to create bootable USB drives”.

#### **Creating a Bootable CD**

Creating a bootable CD is not as simple as creating bootable floppy disks. Refer to any of the following websites for tips on creating bootable CDs. Intel is unable to assist with the creation of bootable devices.

- Bart's Way to Create Bootable CD-ROMs at <http://www.nu2.nu/bootcd/>
- How to Create a Bootable CD-ROM at <http://www.hardwaresecrets.com/article/75>
- How to Create Bootable CDs at <http://www.techsupportalert.com/search/t1214.pdf>

You can also search for additional resources on the web for creating bootable CDs. Search on “How to create a bootable CD”.

---

---

#### LEGAL INFORMATION

**Information in this document is provided in connection with Intel Products and for the purpose of supporting Intel developed server/desktop boards and systems.**

No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted by this document. Except as provided in Intel's Terms and Conditions of Sale for such products, Intel assumes no liability whatsoever, and Intel disclaims any express or implied warranty, relating to sale and/or use of Intel products including liability or warranties relating to fitness for a particular purpose,

---

\*Other names and brands may be claimed as the property of others.

merchantability, or infringement of any patent, copyright or other intellectual property right. Intel Corporation may have patents or pending patent applications, trademarks, copyrights, or other intellectual property rights that relate to the presented subject matter. The furnishing of documents and other materials and information does not provide any license, express or implied, by estoppel or otherwise, to any such patents, trademarks, copyrights, or other intellectual property rights. Intel products are not intended for use in medical, life saving, or life sustaining applications. Intel may make changes to specifications and product descriptions at any time, without notice.

Intel is a registered trademark of Intel Corporation.  
Copyright (c) 2011 Intel Corporation.